
Luminaire
Code 2124010A
Name AoL SYSTEM S CURVA UP 3000K
Measurem.
Code FTS1902573
Name AoL SYSTEM S CURVA UP 3000K


Luminaire Flux	635.58 lm	Luminaire Power	8.00 W	Efficacy	79.45 lm/W	Efficiency	100.00%
Sources Flux	635.58 lm	Maximum value	151.82 cd/klm	Position	C=0.00 G=48.00	CG	Sym. on planes 0-180

Rectangular Luminaire	Length 50 mm		Width 50 mm		Height 580 mm
Rectangular Luminous Area	Length 50 mm		Width 50 mm		Height 580 mm
Horizontal Luminous Area	0.002500 m2		Emitting area on Plane 180°		0.029000 m2
Emitting area on Plane 0°	0.029000 m2		Emitting area on Plane 270°		0.029000 m2
Emitting area on Plane 90°	0.029000 m2		Glare area at 76°		0.028743 m2
Coordinate system	CG		Symmetry Type		Sym. on planes 0-180
Date	13-09-2019		Maximum Gamma Angle		180
Measurement Distance	0.00		Measurement Flux		635.58 lm

LED Flux=903lm LED Power=8W Eff=70% EfcLed=113lm/W EfcLum=79lm/W CCT=3000K Ra=80 SDCM=3 L70(6K)=50000h

C.I.E.	26 52 77 64 100	D DIN 5040	B11
F UTE	0.64 J + 0.36 T	B NBN	BZ 8





ULOR 35.91 %
DLOR 64.09 %
RN 35.91 %

Luminaire
Code 2124010A
Name AoL SYSTEM S CURVA UP 3000K
Measurem.
Code FTS1902573
Name AoL SYSTEM S CURVA UP 3000K

Luminaire Flux	635.58 lm	Luminaire Power	8.00 W	Efficacy	79.45 lm/W	Efficiency	100.00%
Sources Flux	635.58 lm	Maximum value	151.82 cd/klm	Position	C=0.00 G=48.00	CG	Sym. on planes 0-180

Rectangular Luminaire	Length 50 mm	Width 50 mm	Height 580 mm
Rectangular Luminous Area	Length 50 mm	Width 50 mm	Height 580 mm
Horizontal Luminous Area	0.002500 m2	Emitting area on Plane 180°	0.029000 m2
Emitting area on Plane 0°	0.029000 m2	Emitting area on Plane 270°	0.029000 m2
Emitting area on Plane 90°	0.029000 m2	Glare area at 76°	0.028743 m2
Coordinate system	CG	Symmetry Type	Sym. on planes 0-180
Date	13-09-2019	Maximum Gamma Angle	180
Measurement Distance	0.00	Measurement Flux	635.58 lm

LED Flux=903lm LED Power=8W Eff=70% EfcLed=113lm/W EfcLum=79lm/W CCT=3000K Ra=80 SDCM=3 L70(6K)=50000h

C.I.E.	26 52 77 64 100	D DIN 5040	B11
F UTE	0.64 J + 0.36 T	B NBN	BZ 8

Apertura a destra non trovata, gamma =48

Apertura a destra non trovata, gamma =48

Apertura a destra non trovata, gamma =48